

Manu- facturer	IC	Frequency	Model	Load Cap	Part Nr.	Field	Application
Atmel/Microchip	AT89C51RC2	11.0592 MHz	KX-CT	16 pF	12.87319 12.87325 12.87339	Controller	8 Bit
	AT91SAM7S256	9.216 MHz	KX-12AT	16 pF	12.85281	Controller	32 Bit
	ATA8520D_KX-6E	24.3050 MHz	KX-6E	8 pF	12.86635	Wireless	SigFox
	ATA8520D_KX-7T	24.3050 MHz	KX-7T	8 pF	12.60128	Wireless	SigFox
	ATSAM4E16E	12 MHz	KX-7T	12 pF	12.88692	Controller	32 Bit
	ATSAM4SA16C	12 MHz	KX-7T	12 pF	12.88673	Controller	32 Bit
	SAMA5D36_KX-7T	12 MHz	KX-7T	12 pF	12.88673	Controller	32 Bit
	SAMA5D36_KX-327NHT	32.768 kHz	KX-327NHT	12,5 pF	12.87150 12.87157 12.87158 12.87159	Controller	32 Bit
CSR/Qualcomm	CSRB31010_KX-327L	32.768 kHz	KX-327L	9 pF	12.87137	Wireless	Bluetooth
	CSRB31010_KX-327NHT_7pF	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Wireless	Bluetooth
	CSRB31010_KX-327NHT_9pF	32.768 kHz	KX-327NHT	9 pF	12.87149 12.87151	Wireless	Bluetooth
Cypress	EZ-USB_KX-5	24 MHz	KX-5	20 pF	12.85632	Networking	USB
	EZ-USB_KX-7	24 MHz	KX-7	20 pF	12.60052	Networking	USB
Freescale	KinetisKL36-family	32.768 kHz	KX-26T	12.5 pF	12.80115	Controller	32 Bit
	KinetisKL36-family	32.768 kHz	KX-26	12.5 pF	12.80116 12.80128	Controller	32 Bit
	MCiMX283DVM	32.768 kHz	KX-327RT	7 pF	12.87163	Controller	32 Bit
	MCiMX6S5DVM	32.768 kHz	KX-327L	7 pF	12.87132 12.87134 12.87135	Controller	32 Bit
Lantiq	PEF21628E	40.96 MHz	KX-7T	12 pF	12.88586	Networking	HDSL
	PEF7072	25 MHz	KX-7T	12 pF	12.88751	Networking	LAN
Maxim	Max_7037_KX-327LT	32.768 kHz	KX-327LT	12.5 pF	12.87131	Wireless	LoRa
	Max_7037_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87159	Wireless	LoRa
	Max_7037_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87160	Wireless	LoRa
	Max_7037_KX-5T	16 MHz	KX-5T	10 pF	12.85600	Wireless	LoRa
	Max_7037_KX-6T	16 MHz	KX-6T	10 pF	12.86618	Wireless	LoRa
	Max_7037_KX-7T	16 MHz	KX-7T	10 pF	12.88455	Wireless	LoRa
Microchip	16F 182718281938	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	8 Bit
	16LF1936	32.768 kHz	KX-327L	7 pF	12.87132 12.87134 12.87135	Controller	8 Bit
	24FJ64GA306_KX-327FT	32.768 kHz	KX-327FT	12.5 pF	12.87171	Controller	16 Bit
	24FJ64GA306_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87158	Controller	16 Bit
	24FJ64GA306_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Controller	16 Bit
	24FJ64GA306_KX-327VT	32.768 kHz	KX-327VT	12.5 pF	12.87000	Controller	16 Bit
	24FJ64GA306_KX-4T	25 MHz	KX-4T	10 pF	12.84842	Controller	16 Bit

Manufacturer	IC	Frequency	Model	Load Cap	Part Nr.	Field	Application
Microchip	24FJ64GA306_KX-5E	25 MHz	KX-5E	10 pF	12.85585	Controller	16 Bit
	24FJ64GA306_KX-6T	25 MHz	KX-6T	10 pF	12.86599	Controller	16 Bit
	24FJ64GA306_KX-7T	25 MHz	KX-7T	10 pF	12.88786	Controller	16 Bit
	24FJ64GA308_KX-327FT	32.768 kHz	KX-327FT	12.5 pF	12.87171	Controller	16 Bit
	24FJ64GA308_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87158	Controller	16 Bit
	24FJ64GA308_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Controller	16 Bit
	24FJ64GA308_KX-327VT	32.768 kHz	KX-327VT	12.5 pF	12.87000	Controller	16 Bit
	24FJ64GA308_KX-4T	25 MHz	KX-4T	10 pF	12.84842	Controller	16 Bit
	24FJ64GA308_KX-5E	25 MHz	KX-5E	10 pF	12.85585	Controller	16 Bit
	24FJ64GA308_KX-6T	25 MHz	KX-6T	10 pF	12.86599	Controller	16 Bit
	24FJ64GA308_KX-7T	25 MHz	KX-7T	10 pF	12.88786	Controller	16 Bit
	24FJ64GB106_KX-327FT	32.768 kHz	KX-327FT	9 pF	12.87172	Controller	16 Bit
	24FJ64GB106_KX-327NHTT	32.768 kHz	KX-327NHT	9 pF	12.87146	Controller	16 Bit
	24FJ64GB106_KX-327RT	32.768 kHz	KX-327RT	9 pF	12.87165	Controller	16 Bit
	24FJ64GB106_KX-327VT	32.768 kHz	KX-327VT	9 pF	12.87001	Controller	16 Bit
	24FJ64GB106_KX-5T	32 MHz	KX-5T	10 pF	12.85601	Controller	16 Bit
	24FJ64GB106_KX-6T	32 MHz	KX-6T	10 pF	12.86619	Controller	16 Bit
	24FJ64GB106_KX-7T	32 MHz	KX-7T	10 pF	12.60078	Controller	16 Bit
	32MX320F128L	32.768 kHz	KX-327L	12.5 pF	12.87130 12.87131 12.87133 12.87136	Controller	32 Bit
	AVR64DD32	20 MHz	KX-5	12 pF	12.85648	Controller	32 Bit
	AVR64DD32	20 MHz	KX-6	12 pF	12.86503	Controller	32 Bit
	AVR64DD32	20 MHz	KX-7	12 pF	12.88460	Controller	32 Bit
	LAN9512_KX-5T	25 MHz	KX-5T	20 pF	12.85588	Networking	USB, LAN
	LAN9512_KX-7T	25 MHz	KX-7T	20 pF	12.88468	Networking	LAN
	PIC16F1826_27_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	8 Bit
	PIC16F1826_27_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	8 Bit
	PIC16F1826_27_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	8 Bit
	PIC16F1826_27_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	8 Bit
	PIC16F1826_27_KX-5E	20 MHz	KX-5E	12 pF	12.85648	Controller	8 Bit
	PIC16F1826_27_KX-6T	20 MHz	KX-6T	12 pF	12.86633	Controller	8 Bit
	PIC16F1826_27_KX-7T	20 MHz	KX-7T	12 pF	12.60067	Controller	8 Bit
	PIC16LF1934_6_7_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	8 Bit
PIC16LF1934_6_7_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	8 Bit	
PIC16LF1934_6_7_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	8 Bit	
PIC16LF1934_6_7_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	8 Bit	
PIC16LF1934_6_7_KX-5E	20 MHz	KX-5E	12 pF	12.85648	Controller	8 Bit	
PIC16LF1934_6_7_KX-6T	20 MHz	KX-6T	12 pF	12.86633	Controller	8 Bit	
PIC16LF1934_6_7_KX-7T	20 MHz	KX-7T	12 pF	12.60067	Controller	8 Bit	
USB2517_KX-4	24 MHz	KX-4	10 pF	12.84830	Networking	USB, LAN	
USB2517_KX-5	24 MHz	KX-5	10 pF	12.85502	Networking	USB, LAN	
USB2517_KX-6	24 MHz	KX-6	10 pF	12.86546	Networking	USB, LAN	
USB2517_KX-7	24 MHz	KX-7	10 pF	12.60159	Networking	USB, LAN	
Nordic	nRF52810_KX-327FT	32.768 kHz	KX-327FT	12.5 pF	12.87171	Wireless	Bluetooth
	nRF52810_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87158	Wireless	Bluetooth
	nRF52810_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Wireless	Bluetooth
	nRF52810_KX-327VT	32.768 kHz	KX-327VT	12.5 pF	12.87000	Wireless	Bluetooth
	nRF52810_KX-5T	32 MHz	KX-5T	12 pF	12.85595	Wireless	Bluetooth

Manufacturer	IC	Frequency	Model	Load Cap	Part Nr.	Field	Application
Nordic	nRF52810_KX-7T	32 MHz	KX-7T	12 pF	12.60189	Wireless	Bluetooth
	nRF52832_KX-327FT	32.768 kHz	KX-327FT	12.5 pF	12.87171	Wireless	Bluetooth
	nRF52832_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87158	Wireless	Bluetooth
	nRF52832_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Wireless	Bluetooth
	nRF52832_KX-327VT	32.768 kHz	KX-327VT	12.5 pF	12.87000	Wireless	Bluetooth
	nRF52832_KX-5T	32 MHz	KX-5T	12 pF	12.85595	Wireless	Bluetooth
	nRF52832_KX-7T	32 MHz	KX-7T	12 pF	12.60189	Wireless	Bluetooth
	nRF52840_KX-327FT	32.768 kHz	KX-327FT	12.5 pF	12.87171	Wireless	Zigbee, Bluetooth
	nRF52840_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87158	Wireless	Zigbee, Bluetooth
	nRF52840_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Wireless	Zigbee, Bluetooth
	nRF52840_KX-327VT	32.768 kHz	KX-327VT	12.5 pF	12.87000	Wireless	Zigbee, Bluetooth
	nRF52840_KX-5T	32 MHz	KX-5T	12 pF	12.85595	Wireless	Zigbee, Bluetooth
	nRF52840_KX-7T	32 MHz	KX-7T	12 pF	12.60189	Wireless	Zigbee, Bluetooth
	nRF8001	16 MHz	KX-7	9 pF	12.88785	Wireless	Bluetooth
nRF8001	32.768 kHz	KX-327NHT	9 pF	12.87149 12.87151	Wireless	Bluetooth	
nRF8001	32.768 kHz	KX-327NHF	9 pF	12.87181	Wireless	Bluetooth	
NXP	NXP-MC9S12DG128_KX-5T	16 MHz	KX-5T	10 pF	12.85600	Controller	16 Bit
	NXP-MC9S12DG128_KX-6T	16 MHz	KX-6T	10 pF	12.86618	Controller	16 Bit
	NXP-MC9S12DG128_KX-7T	16 MHz	KX-7T	10 pF	12.88455	Controller	16 Bit
	NXP-MC9S12XDT256_KX-5T	16 MHz	KX-5T	10 pF	12.85600	Controller	16 Bit
	NXP-MC9S12XDT256_KX-6T	16 MHz	KX-6T	10 pF	12.86618	Controller	16 Bit
	NXP-MC9S12XDT256_KX-7T	16 MHz	KX-7T	10 pF	12.88455	Controller	16 Bit
Renesas	M38238G8	10 MHz	KX-7T	16 pF	12.88771	Controller	8 Bit
	M38238G8	32.768 kHz	KX-327FT	12,5 pF	12.87171	Controller	8 Bit
	M38238G8	32.768 kHz	KX-327NHT	12,5 pF	12.87167	Controller	8 Bit
	M38238G8	32.768 kHz	KX-327RT	12,5 pF	12.87158	Controller	8 Bit
	M38238G8	32.768 kHz	KX-327VT	12,5 pF	12.87000	Controller	8 Bit
	RL78-11B_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	RL78-11B_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
	RL78-11B_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	RL78-11B_KX-6T	12 MHz	KX-6T	10 pF	12.86622	Controller	16 Bit
	RL78-11B_KX-7T	12 MHz	KX-7T	10 pF	12.88595	Controller	16 Bit
UPD78F0485GK 8bit MCU	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	8 Bit	
Semtech	SX1238_KX-5T	32 MHz	KX-5T	10 pF	12.85601	Wireless	Zigbee
	SX1238_KX-6T	32 MHz	KX-6T	10 pF	12.86619	Wireless	Zigbee
	SX1238_KX-7T	32 MHz	KX-7T	10 pF	12.60078	Wireless	Zigbee
	SX1272 73	32 MHz	KX-7T	12 pF	12.60030 12.88562 12.88599	Wireless	LoRa
	SX1276 77 78 79	32 MHz	KX-7	12 pF	12.60030 12.88562 12.88599	Wireless	LoRa
	TS80000	8 MHz	KX-7T	8 pF	12.60022	Diverse	Wireless Power
	TS800006	13.560 MHz	KX-7T	12 pF	12.60072 12.88561 12.88504	Diverse	Wireless Power
SiLabs	EFM32GG890F1024	32.768 kHz	KX-327LT	12.5 pF	12.87131	Controller	32 Bit
	EFM32GG890F1024_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87145 12.87159	Controller	32 Bit

Manu- facturer	IC	Frequency	Model	Load Cap	Part Nr.	Field	Application
Silabs	EFM32GG890F1024_KX-7T	48 MHz	KX-7T	12 pF	12.88710	Controller	32 Bit
	EFM32LG230	32.768 kHz	KX-327VT	12.5 pF	12.87000	Controller	32 Bit
	EM351 EM357 kHz	32.768 kHz	KX-327LT	12.5 pF	12.87130 12.87159	Wireless	Zigbee
	EM351 EM357 MHz	24 MHz	KX-7T	18 pF	12.60029 12.88587	Wireless	Zigbee
STMicroelectronics	32F072	32.768 kHz	KX-327NHT	12.5 pF	12.87150 12.87157 12.87158 12.87159	Controller	32 Bit
	32F072	32.768 kHz	KX-327NHF	12.5 pF	12.87180	Controller	32 Bit
	32F091	32.768 kHz	KX-327NHT	12.5 pF	12.87150 12.87157 12.87158 12.87159	Controller	32 Bit
	32F091	32.768 kHz	KX-327NHF	12.5 pF	12.87180	Controller	32 Bit
	32F101	32.768 kHz	KX-327L	7 pF	12.87132 12.87134 12.87135	Controller	32 Bit
	32F103	32.768 kHz	KX-327L	7 pF	12.87132 12.87134 12.87135	Controller	32 Bit
	32F103	8 MHz	KX-7T	12 pF	12.60028	Controller	32 Bit
	32F103	32.768 kHz	KX-327NHT	7 pF	12.87153	Controller	32 Bit
	32F103	32.768 kHz	KX-327NHT	12.5 pF	12.87150 12.87157 12.87158 12.87159	Controller	32 Bit
	32F103	32.768 kHz	KX-327NHF	12.5 pF	12.87180	Controller	32 Bit
	32F103	8.192 MHz	KX-9AE	16 pF	12.89125	Controller	32 Bit
	32F103	8 MHz	KX-9AE	16 pF	12.89112	Controller	32 Bit
	32F2x5	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	32 Bit
	32F301	32.768 kHz	KX-327L	12.5 pF	12.87130 12.87131 12.87133 12.87136	Controller	32 Bit
32F334	32.768 kHz	KX-327NHT	12.5 pF	12.87150 12.87158 12.87159	Controller	32 Bit	
32F334	32.768 kHz	KX-327NHF	12.5 pF	12.87180	Controller	32 Bit	
32F401	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	32 Bit	
32F417	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	32 Bit	
32F427	32.768 kHz	KX-327RT	12.5 pF	12.87160 12.87167	Controller	32 Bit	
32F429	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	32 Bit	

Manufacturer	IC	Frequency	Model	Load Cap	Part Nr.	Field	Application
STMicroelectronics	32F440	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	32 Bit
	32L051	32.768 kHz	KX-327RT	9 pF	12.87164 12.87165	Controller	32 Bit
	32L053	32.768 kHz	KX-327NHT	7 pF	12.87147 12.87148 12.87153	Controller	32 Bit
	32L152	32.768 kHz	KX-327L	7 pF	12.87132 12.87134 12.87135	Controller	32 Bit
	STM8L052C6_KX-327NHT	32.768 kHz	KX-327NHT	6 pF	12.87083	Controller	8 Bit
	STM8L052C6_KX-6T	16 MHz	KX-6T	8 pF	12.86560	Controller	8 Bit
	STM8L052C6_KX-7T	16 MHz	KX-7T	8 pF	12.88765	Controller	8 Bit
Texas Instruments	CC1110_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87159	Wireless	Wireless MCU
	CC1110_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87160	Wireless	Wireless MCU
	CC1110_KX-5T	26 MHz	KX-5T	12 pF	12.85635	Wireless	Wireless MCU
	CC1110_KX-7T	26 MHz	KX-7T	12 pF	12.60171	Wireless	Wireless MCU
	CC1111_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87159	Wireless	Wireless MCU
	CC1111_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87160	Wireless	Wireless MCU
	CC1111_KX-7T	48 MHz	KX-7T	16 pF	12.60191	Wireless	Wireless MCU
	CC1200_KX-5T	40 MHz	KX-5T	10 pF	12.85592	Wireless	Wireless MCU
	CC1200_KX-6T	40 MHz	KX-6T	10 pF	12.86562	Wireless	Wireless MCU
	CC1200_KX-7T	40 MHz	KX-7T	10 pF	12.60113	Wireless	Wireless MCU
	CC1310_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87174	Wireless	Wireless MCU
	CC1310_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87148	Wireless	Wireless MCU
	CC1310_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87163	Wireless	Wireless MCU
	CC1310_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Wireless	Wireless MCU
	CC1310_KX-7T	24 MHz	KX-7T	8 pF	12.88548	Wireless	Wireless MCU
	CC2541_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87159	Wireless	Bluetooth
	CC2541_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87160	Wireless	Bluetooth
	CC2541_KX-327VT	32.768 kHz	KX-327VT	12.5 pF	12.87000	Wireless	Bluetooth
	CC2541_KX-5T	32 MHz	KX-5T	10 pF	12.85601	Wireless	Bluetooth
	CC2541_KX-6T	32 MHz	KX-6T	10 pF	12.86619	Wireless	Bluetooth
	CC2541_KX-7T	32 MHz	KX-7T	10 pF	12.60078	Wireless	Bluetooth
	CC2650_KX-327FT	32.768 kHz	KX-327FT	9 pF	12.87172	Wireless	Zigbee, Bluetooth
	CC2650_KX-327NHT	32.768 kHz	KX-327NHT	9 pF	12.87146	Wireless	Zigbee, Bluetooth
	CC2650_KX-327RT	32.768 kHz	KX-327RT	9 pF	12.87165	Wireless	Zigbee, Bluetooth
	CC2650_KX-327VT	32.768 kHz	KX-327VT	9 pF	12.87001	Wireless	Zigbee, Bluetooth
	CC2650_KX-7T	24 MHz	KX-7T	9 pF	12.60138	Wireless	Zigbee, Bluetooth
	MSP430F2370_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit
	MSP430F2370_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	MSP430F2370_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
	MSP430F2370_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	MSP430F2417_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit
	MSP430F2417_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	MSP430F2417_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
MSP430F2417_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit	
MSP430F449_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit	
MSP430F449_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit	
MSP430F449_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit	

Manu- facturer	IC	Frequency	Model	Load Cap	Part Nr.	Field	Application
Texas Instruments	MSP430F449_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	MSP430F4783_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit
	MSP430F4783_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	MSP430F4783_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
	MSP430F4783_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	MSP430F6747_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87145	Controller	16 Bit
	MSP430F6747_KX-327RT	32.768 kHz	KX-327RF	12.5 pF	12.87167	Controller	16 Bit
	MSP430FG4270_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit
	MSP430FG4270_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	MSP430FG4270_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
	MSP430FG4270_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	MSP430FR5847_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87145	Controller	16 Bit
	MSP430FR5847_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Controller	16 Bit
	MSP430FR5949_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87145	Controller	16 Bit
	MSP430FR5949_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Controller	16 Bit
	MSP430FR692x_KX-327NHT	32.768 kHz	KX-327NHT	12.5 pF	12.87145	Controller	16 Bit
	MSP430FR692x_KX-327RT	32.768 kHz	KX-327RT	12.5 pF	12.87167	Controller	16 Bit
	MSP430G255_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit
	MSP430G255_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	MSP430G255_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
	MSP430G255_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	MSP430P325_KX-327FT	32.768 kHz	KX-327FT	7 pF	12.87175	Controller	16 Bit
	MSP430P325_KX-327NHT	32.768 kHz	KX-327NHT	7 pF	12.87147	Controller	16 Bit
	MSP430P325_KX-327RT	32.768 kHz	KX-327RT	7 pF	12.87033	Controller	16 Bit
	MSP430P325_KX-327VT	32.768 kHz	KX-327VT	7 pF	12.87002	Controller	16 Bit
	TI-ADS1216		4.9152 MHz	KX-KT	16 pF	12.88280	Diverse
TI-TMS320F280		20 Mhz	KX-7T	12 pF	12.60067	Diverse	DSP